

BKITXS822 Spectrum LV Plug & Play Freestanding Spots



Spectrum LED Plug & Play Freestanding Kits

from Display Lighting incorporate robust, high quality and hard wearing freestanding spotlights that are manufactured in the UK and very easy to set up using simple plug & play barrel connectors meaning there is zero wiring required. BKIT's are supplied with mains power adapters and lithium batteries for operating the spotlights when there is no access to mains power. The pure design ensures that the spotlights are as unobtrusive as possible so that your products are illuminated to their full potential without obstruction. The kits are supplied with a choice of 3000K, 4000K or 6500K LED lamps that produce over 450lm each and are easy to replace.

- Available in kits of 1, 2, 3 or 4 spotlights.
- Plug & Play for quick set up in exhibition & event displays.
- Low heat illumination.
- No ultraviolet light so does not fade materials.
- Unobtrusive.

Technical Specifications

Kit Codes:	BKIT1XS822 - 1 Spot Plug & Play Kit BKIT2XS822 - 2 Spot Plug & Play Kit BKIT3XS822 - 3 Spot Plug & Play Kit BKIT4XS822 - 4 Spot Plug & Play Kit
Head Diameter:	25mm
Height:	75mm
Material/s:	Brass
Electrical Connection/s:	Plug & Play 2.1mm DC Barrel Connectors
Lead Length:	1800mm (1m, 3m & 5m Extensions available separately)
CCT (Lumens):	WW - 3000K (450lm CRI80>) CW - 4000K (480lm CRI80>) DW - 6500K (480lm CRI80>)
Watts:	5W (MR16 G5.3 LED Lamp)
Fixing:	Freestanding
Class:	III
IP Rating:	IP20
Rotation Tilt:	350 Degrees 90 Degrees
Finishes:	01 - White 02 - Black 03 - Polished Chrome 04 - Polished Brass/Lacquer 05 - Brushed Chrome 06 - Antique Brass/Lacquer 07 - Polished Nickel 08 - Brushed Nickel 15 - Brushed Brass/Lacquer 16 - Copper RAL - RAL Colours
Input Voltage:	12VDC (constant voltage)
Beam Angle:	36 Degrees
Warranty:	2 Years
Dimming:	Not dimmable
Ordering:	3 step order code (see page 6)
Lithium Battery Options:	DLT2541/X (4aH Rechargeable Lithium Polymer Battery Add-On) DLT2544/X (8aH Rechargeable Lithium Polymer Battery Add-On) DLT2545/X (10aH Rechargeable Lithium Polymer Battery Add-On) DLT2546/X (14aH Rechargeable Lithium Polymer Battery Add-On) DLT2548/X (22aH Rechargeable Lithium Polymer Battery Add-On)

BKIT1XS822 - 1 Spot Kit



1 x Spectrum LV Pro Freestanding Spotlight
1 x MR16 Replaceable COB LED Lamp
1 x Mains Power Supply

+ RECHARGEABLE LITHIUM BATTERY PACK:

DLT2541/5 8 Hours (4aH)
DLT2544/5 17 Hours (8aH)
DLT2545/5 21 Hours (10aH)
DLT2546/5 30 Hours (14aH)
DLT2548/5 47 Hours (22aH)

BKIT2XS822 - 2 Spot Kit



2 x Spectrum LV Pro Freestanding Spotlights
2 x MR16 Replaceable COB LED Lamps
1 x Mains Power Supply

+ RECHARGEABLE LITHIUM BATTERY PACK:

DLT2541/6 4 Hours (4aH)
DLT2544/6 8 Hours (8aH)
DLT2545/6 10 Hours (10aH)
DLT2546/6 14 Hours (14aH)
DLT2548/6 23 Hours (22aH)

BKIT3XS822 - 3 Spot Kit



3 x Spectrum LV Pro Freestanding Spotlights
3 x MR16 Replaceable COB LED Lamps
1 x Mains Power Supply

+ RECHARGEABLE LITHIUM BATTERY PACK:

DLT2541/7 2 Hours (4aH)
DLT2544/7 5 Hours (8aH)
DLT2545/7 7 Hours (10aH)
DLT2546/7 10 Hours (14aH)
DLT2548/7 15 Hours (22aH)

BKIT4XS822 - 4 Spot Kit



4 x Spectrum LV Pro Freestanding Spotlights
4 x MR16 Replaceable COB LED Lamps
1 x Mains Power Supply

+ RECHARGEABLE LITHIUM BATTERY PACK:

DLT2541/8 2 Hours (4aH)
DLT2544/8 4 Hours (8aH)
DLT2545/8 5 Hours (10aH)
DLT2546/8 7 Hours (14aH)
DLT2548/8 11 Hours (22aH)

BKITS822 Spectrum LV Plug & Play Freestanding Spots

THREE STEP ORDERING

	1	2	3
KIT CODE	CCT	FINISH	BATTERY OPTION
BKIT1XS822	WW	01	DLT2541/5 - 1 Spot
BKIT2XS822	CW	02	DLT2544/5 - 1 Spot
BKIT3XS822	DW	03	DLT2545/5 - 1 Spot
BKIT4XS822		04	DLT2546/5 - 1 Spot
		05	DLT2548/5 - 1 Spot
		06	DLT2541/6 - 2 Spots
		07	DLT2544/6 - 2 Spots
		08	DLT2545/6 - 2 Spots
		15	DLT2546/6 - 2 Spots
		16	DLT2548/6 - 2 Spots
		RAL	DLT2541/7 - 3 Spots
			DLT2544/7 - 3 Spots
			DLT2545/7 - 3 Spots
			DLT2546/7 - 3 Spots
			DLT2548/7 - 3 Spots
			DLT2541/8 - 4 Spots
			DLT2544/8 - 4 Spots
			DLT2545/8 - 4 Spots
			DLT2546/8 - 4 Spots
			DLT2548/8 - 4 Spots

Example Order Code: BKIT2XS822.CW.03.DLT2548/6